

Syntax is: device = prspf.sys [/P=1] /T1=3H

P=Port

1=LPT1:

2=LPT2:

T1=Type of 1st Drive. T2=Type of 2nd drive.

3L=3.5" Low Density Drive (720Kb) /N:9/T:80

3H=3.5" High Density Drive (720Kb/1.44Mb) /N:18/T:80

3E=3.5" Extra High Density (720Kb/1.44Mb/2.88Mb) /N:36/T:80

5L=5.25" Low Density Drive (360Kb) /N:9/T:40

5H=5.25" High Density Drive (360Kb/1.2Mb) /N:15/T:80

NOTES:

DR DOS 6.0

FORMATTING DISKETTES

In some situations when attempting to format diskettes an error message may indicate that the diskette is formatted using another system and/or the diskette is unusable. It may be necessary to use the following syntax: (assuming the drive is drive "D:")

720Kb 3.5" diskettes - FORMAT D:/N:9/T:80

1.44mB 3.5" diskettes - FORMAT D:/N:18/T:80

360Kb 5.25" diskettes - FORMAT D:/N:9/T:40

1.2Mb 5.25" diskettes - FORMAT D:/N:15/T:80

To use this software on Hewlett-Packard's OmniBook 300, it must first be transferred from another computer via Laplink into the root directory of the boot drive. Then use the syntax above to install into the config.sys file, or run the install program, which will make the insertion for you.